

This Page Is Inserted by IFW Operations
and is not a part of the Official Record

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images may include (but are not limited to):

- BLACK BORDERS
- TEXT CUT OFF AT TOP, BOTTOM OR SIDES
- FADED TEXT
- ILLEGIBLE TEXT
- SKEWED/SLANTED IMAGES
- COLORED PHOTOS
- BLACK OR VERY BLACK AND WHITE DARK PHOTOS
- GRAY SCALE DOCUMENTS

IMAGES ARE BEST AVAILABLE COPY.

**As rescanning documents *will not* correct images,
please do not report the images to the
Image Problem Mailbox.**

What is claimed is:

1. A laser diode drive circuit for an optical disc recording and/or reproducing apparatus, comprising:

a plurality of laser diodes for outputting laser beams having different wavelengths;

a switch circuit for selectively connecting a required laser diode from said plurality of laser diodes;

a laser diode drive power supply circuit for driving the laser diode selectively connected by said switch circuit;

a photodiode for detecting at least part of laser beams emitted from said laser diode to convert a detected part of laser beams into an electrical signal;

a plurality of current-to-voltage conversion amplifiers connected to an output of said photodiode, being capable of adjusting conversion resistance values and having differently designed center conversion resistance values; and

an automatic power control circuit connected to outputs of said current-to-voltage conversion amplifiers to output a feedback signal to said laser diode drive power supply circuit.

2. The laser diode drive circuit for an optical disc recording and/or reproducing apparatus according to claim 1, wherein

said photodiode is composed of a single diode and switch circuits for selectively connecting a required current-to-voltage conversion amplifier are provided both between an output of said photodiode and inputs of said plurality of current-to-voltage conversion amplifiers, and between outputs of said plurality of current-to-voltage conversion amplifiers and an input of said automatic power control circuit.

3. The laser diode drive circuit for an optical disc recording and/or reproducing apparatus according to claim 1, wherein

said photodiode is composed of a plurality of diodes,

outputs of said respective diodes are connected to inputs of corresponding current-to-voltage conversion amplifiers of said plurality of current-to-voltage conversion amplifiers respectively and

switch circuits for selectively connecting required current-to-voltage conversion amplifiers are provided between outputs of said plurality of current-to-voltage conversion amplifiers and an input of said automatic power control circuit.

4. An amplifying circuit comprising:

a plurality of current-to-voltage conversion amplifiers connected in parallel, being capable of

adjusting conversion resistance values and having differently designed center conversion resistance values; and

change-over switches provided at the input sides and output sides of said plurality of current-to-voltage conversion amplifiers, whereby one amplifier is selectively connected under change-over control of said switches.

5. An optical disc recording and/or reproducing apparatus including a laser diode drive circuit, said laser diode drive circuit comprising:

a plurality of laser diodes for outputting laser beams having different wavelengths;

a switch circuit for selectively connecting a required laser diode from said plurality of laser diodes;

a laser diode drive power supply circuit for driving the laser diode selectively connected by said switch circuit;

a photodiode for detecting at least part of laser beams emitted from said laser diode to convert a detected part of laser beams into an electrical signal;

a plurality of current-to-voltage conversion amplifiers connected to an output of said photodiode, being capable of adjusting conversion resistance values and having differently designed center conversion resistance values; and

an automatic power control circuit connected to

outputs of said current-to-voltage conversion amplifiers to output a feedback signal to said laser diode drive power supply circuit.

6. A laser diode drive method for an optical disc recording and/or reproducing apparatus, comprising the steps of:

selectively connecting a laser diode from a plurality of laser diodes having different output wavelengths to a laser diode drive power supply circuit with a first switch circuit;

driving said laser diode drive power supply circuit to allow the connected laser diode to emit laser beams;

detecting at least part of laser beams emitted from said laser diode to convert said detected part of laser beams into an electrical signal by a photodiode;

outputting said electrical signal to a corresponding current-to-voltage conversion amplifier of a plurality of current-to-voltage conversion amplifiers, the corresponding amplifier being capable of adjusting conversion resistance values and having differently designed center conversion resistance values, wherein said electrical signal is current-to-voltage-converted and is amplified;

selectively connecting an output of a required current-to-voltage conversion amplifier from said plurality of current-to-voltage conversion amplifiers to an automatic

power control circuit with a second switch circuit;

generating a feedback signal from said electrical signal, which has been current-to-voltage-converted and amplified, by said automatic power control circuit; and

outputting said feedback signal to said laser diode drive power supply circuit to effect a closed loop control.